



StreetSiren Jeweller

Wireless siren with LED frame.

An Ajax hub is required for operation.



Key features

Adjustable volume: from 85 dB to 113 dB

Adjustable alarm duration: from 3 to 180 s

Delay and security mode changing indication

Door opening notifications

IP54 protection class

Effortless installation and replacement

Remote control and setup via the app

Connecting via QR code

Operating principle




Informs about alarms

The siren responds to tamper and security system alarms in less than a second. It is loud enough to scare away intruders and attract the attention of neighbours.

Serves as a security status indicator

The siren LED notifies that the facility is armed, and a sound signal indicates Delay When Entering / Leaving. These are helpful features for the users who control the security system with a keypad or key fob.



Informs about alarms

The siren responds to tamper and security system alarms in less than a second. It is loud enough to scare away intruders and attract the attention of neighbours.



Jeweller
communication technology



Jeweller is a two-way wireless protocol that provides fast and reliable communication between hubs and devices. The protocol delivers instant data-rich alarms: security companies and users know who and when has armed or disarmed the facility.

Jeweller features encryption and authentication to prevent forgery, and polling to display devices' status in real-time. Supporting up to 1,500 m of wireless connectivity between StreetSiren and hub (or range extender), Jeweller is ready to protect facilities and deliver the best user experience for both end-users and installers.

Technical specifications

Compliance with standards

EN 50131 (Grade 2) PD 6662:2017

Compatibility

Hubs
all Ajax hubs

Range extenders
all Ajax radio signal range extenders

Communication with control panel and range extenders	<p>Jeweller communication technology</p> <p>Frequency bands</p> <p>866.0 – 866.5 MHz</p> <p>868.0 – 868.6 MHz</p> <p>868.7 – 869.2 MHz</p> <p>905.0 – 926.5 MHz</p> <p>915.85 – 926.5 MHz</p> <p>921.0 – 922.0 MHz</p> <p>Depends on the region of sales.</p> <p>Maximum effective radiated power (ERP) ≤ 20 mW</p> <p>Communication range up to 1,500 m In an open space.</p> <p>Polling interval 12 – 300 s Adjusted by PRO or user with admin rights in the Ajax app.</p> <p>Protection against forgery Device authentication</p> <p>Main power supply</p>	Features	<p>Alarm type acoustic and light</p> <p>Alarm volume from 85 to 113 dB at a distance of 1 m Adjusted by PRO or user with admin rights in the Ajax app.</p> <p>Alarm duration from 3 to 180 s Adjusted by PRO or user with admin rights in the Ajax app.</p> <p>Siren sound frequency 3.5 ± 0.5 kHz</p> <p>Chime The siren makes a special sound to notify that the opening detectors are triggered when the system is disarmed.</p>
Power supply	<p>4 × CR123A battery Pre-installed</p> <p>Optional power supply 12 V⎓, 1.5 A</p> <p>Battery life up to 5 years</p>	Installation	<p>Operating temperature range from -25°C to +60°C</p> <p>Operating humidity up to 95%</p> <p>Protection class IP54</p>

Enclosure	Colours white, black	Complete set	StreetSiren Jeweller 4 × CR123A battery Pre-installed SmartBracket Installation kit Quick Start Guide
	Dimensions 75 × 76 × 27 mm		
	Weight 97 g		
	Anti-sabotage tampering alarm Triggered when the device body is opened.		
	accelerometer Activated when someone's try to move or dismount the device.		
