

ReX

Radio signal range extender boosting the range of Ajax security system devices that uses Jeweller communication protocol.

An Ajax hub is required for operation.



Key features



Frequency hopping against jamming



Tampering alarm for lid protection



Up to 35 hours on the back-up battery in case of external power loss



Over-the-air updates



Fast connection with security system via QR code



Remote control and setup via Ajax apps

Security for large and complex facilities




The maximum range of radio communication with connected devices is 1700 meters without obstacles. Up to 5 range extenders can be connected to the Ajax security system. It allows using Ajax products for large-scale facilities protection. Regardless of the number of devices connected to the ReX, alarms are delivered in 0.3 seconds.


Encrypted two-way communication

Jeweller is a two-way wireless protocol that provides fast and reliable communication between both: hub and ReX, and ReX and connected devices. The protocol delivers instant data-rich alarms and events: security companies and users know which device was triggered, when and where it happened.

Jeweller features encryption and authentication to prevent forgery, and polling to display connected devices statuses. Supporting up to 1,800 m of wireless connectivity, Jeweller is ready to protect facilities and deliver the best user experience for both end users and installers.

 ReX connects to the hub only directly. Connection to another range extender is not provided.

 Up to 1,800 m communication range

 Alarms and events delivery in 0.3 s

Quick installation

Connecting and configuring ReX is a straightforward process that saves the installer time. To add the range extender to the system, just scan a QR code in the Ajax app and assign a name, room, and group to the device. If necessary, the installer can deactivate or reconfigure ReX remotely without visiting the facility.



Technical specifications

| | | | |
|---------------------------|---------------------------------|---------------|---|
| Compliance with standards | EN 50131 (Grade 2) PD 6662:2017 | Compatibility | Hubs all Ajax hubs |
| | | | Range extenders Connection to another range extender is not provided |

| | | | |
|--|--|--------------|--|
| Communication with control panel and range extenders | <p>Jeweller communication technology</p> <p>Frequency bands</p> <p>866.0 – 866.5 MHz</p> <p>868.0 – 868.6 MHz</p> <p>868.7 – 869.2 MHz</p> <p>905.0 – 926.5 MHz</p> <p>915.85 – 926.5 MHz</p> <p>921.0 – 922.0 MHz</p> <p>Depends on the region of sales</p> <p>Maximum effective radiated power (ERP)</p> <p>≤ 20 mW</p> <p>Communication range</p> <p>up to 1,800 m</p> <p>In an open space</p> <p>Polling interval</p> <p>12–300 s</p> <p>Adjusted by PRO or user with admin rights in the Ajax app</p> <p>Alarms and events delivery speed</p> <p>0.3 s</p> <p>Protection against forgery</p> <p>Device authentication</p> <p>Protection against jamming</p> <p>Frequency hopping</p> <p>Operating temperature range</p> | Power supply | <p>Main power supply</p> <p>110–240 V~, 50/60 Hz</p> <p>Backup power supply</p> <p>Li-Ion 2 Ah</p> <p>Up to 35 hours of autonomous operation</p> |
| Installation | <p>from –10°C to +40°C</p> <p>Operating humidity</p> <p>up to 75%</p> | Enclosure | <p>Colours</p> <p>white, black</p> <p>Dimensions</p> <p>163 × 163 × 36 mm</p> |

| | | | |
|--------------|---|-----------|--|
| Installation | Protection class IP50 | Enclosure | Weight 330 g Tampering alarm |
| Complete set | ReX Jeweller SmartBracket mounting panel Power supply cable Installation kit Quick start guide | | |